

## **Self-Contained Emergency Luminaires**



## 2 x 1.0 w Power LED



## **Specifications**

Model ····· TEL-30 LED Mode ..... Non-Maintained Weight ..... → 1.9 Kg Battery ..... 3 cells 2.5Ah Nickel Cadmium Housing ..... Electro-galvanised sheet steel with powder coated paint Charger ••••• Constant Current Mounting ..... Surface mounting direct to wall Dimension (mm) ..... 295 (L) x 150 (W) x 76 (H) Monitoring ..... Red LED indicating healthy supply and charging Compliance ..... SIRIM MS 619, Jabatan Bomba Light Source ..... 2 x 1W Power LED (Warm White) **⇒** 240 V +/- 10% 50/60 Hz Input Voltage ..... Recharge Period ..... 16 - 24 Hours Back Up Duration ...... 3 Hours



Degree of Protection ..... ⊃ IP - 20

Operating Temperature ••••• \$\(\sigma\) 0° C to 65° C

For further enquiries, please contact :-

## PNE SYSTEMS SDN. BHD. (263861 D)

No.3, Jalan SS26/13,

Taman Mayang Jaya 47301, Petaling Jaya, Selangor Darul Ehsan, Malaysia

Tel: 603-78037488 (Hunting)

Fax: 603-78038509

E-mail: sales@pnesys.com.my Website: www.pnesys.com.my